

Porthaux2-O-Kampmann-Wg1-WOB-DNM

	A	B	C	D	E	F	G	H
1	I. Bocal		Original bocal; Porthaux2 no					
2	dia reed end		inside diameter of reed end of bocal					
3	bocal string length (0, 1)		length of bocal inserted into receiver					
4	metal bocal length top (0, 1)		meas. along top of bocal					
5	metal bocal length bot (0, 1)		meas. along bottom of bocal					
6	dia wj end		inside diameter of bocal					
7								
8	bocal logic	2	if bocal logic = 0 => bocal is choke; if bocal logic = 1 =>choke in wing joint calc; if bocal logic = 2 => no bocal					
9								
10								
11								
12								
13	II. Wing Joint Lengths		bocal receiver: Porthaux2 no; just a slight shelf probably from inserting the bocal					
14	choke bore dia.	9.1	logic 1; bore diameter of choke; logic 0; either diameter bocal bottom or beginning of bore at bottom or receiver					
15	receiver length (1, 0) (formally choke length)	39	logic 1; length of choke from top of wing joint; logic 0; length of receiver (same as string length)					
16	wing joint length	498	total wing joint length, including tenon and socket					
17	tenon length	50.4	tenon length					
18								
19	wj f2	214	dist top of wing to where tone hole enters bore [not at the center of the tone hole]					
20	wj e	287						
21	wj d	329						
22								
23	Bore dia. Bottom of wing joint	15.5	Need to Average, usually oval; Porthaux2 yes, slightly					
24	Bore dia. top of boot joint small side	15.1						
25	Bore dia. top of boot joint large side	24.4						
26								
27	III. Boot Lengths							
28	bj logic	1	logic=> if bj logic = 0 => plug removed; if bj logic = 1 => plug cannot be removed					
29	bj c	88	dist from top of boot to where topmost tone hole enter bore [not at center of tone hole]					
30	bj b	153						
31	bj a	198						
32								
33	bjstotal [Needed for both boot logics]	435	total length of boot, include socket, along the small bore side					
34	bjltotal [Needed for both boot logics]	435	total length of boot, include socket, along large bore side					
35	plug small [Need for logic 0 only]	0	plug thickness, large bore side					
36	plug large [Need for logic 0 only]	0	plug thickness, small bore side					
37								
38	boots [Needed for both boot logics]	389	hook length along s bore => bjs-septum length = boot - septum <= calc the septum					
39	bootl [Needed for both boot logics]	389	hook length along l bore => bjl-septum length = boot - septum <= calc the septum					
40								
41	boots bottom [Needed for both boot logics]	17	use hook, dist of bore [dist on stick plus 7mm, diff between hook and bot of stick]					
42	bootl bottom [Needed for both boot logics]	17	use hook, dist of bore [same as boots bot except tenon depth will be different]					
43			Porthaux2 could not remove boot cap					
44	extreme bore [Needed for logic 1 only]	45.5	Porthaux2 an estimate could not remove boot cap; Outside dia of plug[measured]=small bore dia+large bore dia+the septum width					
45								
46	septum length exp [Need for logic 0 only]	0	dist. from very bottom of boot to septum [point between the large and small bore]					
47	septum length calc - do not imput value	46	dist. From very bottom of boot to septum [bjl - bootl]	do not imput value				
48	septum length - do not imput value	46	if bj logic = 0 => septum = septum exp; if bj logic = 1 => septum = septum calc	do not imput value				
49								
50	sbore dia sep* [Needed for both boot logics]	17.8	septum small bore dia [assume = lbore dia sep]					
51	lbore dia sep* [Needed for both boot logics]	19	septum large bore dia [assume = sbore dia sep] [mesure if cork can be removed; for Logic 0]					
52	sep width exp [Need for logic 0 only]	0	septum width; direct measurement if remove plug					
53	sep width calc - do not imput value	8.7	septum width; calc. => extreme bore - sbore - lbore	do not imput value				
54	sep width - do not imput value	8.7	if bj logic = 0 => sep width = sep width exp; if bj logic = 1 => sep width = sep width calc	do not imput value				
55								
56	bj g	333	dist from top of boot (socket) to where G hole enters bore [not at cent of tone hole]					
57	bj f1	146	dist from top of boot (socket) to where F1 hole enters bore [not at cent of tone hole]					
58								
59								
60								
61								
62								
63	IV. Tone Hole Diameters							
64	f2	5.6						
65	e	6.3						
66	d	5.6						
67								
68	c	7.3						
69	b	6.8						
70	a	6.4						
71	g	9						
72	f1	8.3						
73								
74	e1	13.9	Porthaux2 oblong; e1 tone hole dia, on long joint [need to average NS and EW dias, NS usually greater]					
75	d1	7.5	d1 tone hole dia, on long joint [need to average NS and EW dias, NS usually greater]					
76	c1	15.2	Porthaux2 oblong 14.8 x 15.7; c1 tone hole dia, on long joint [need to average NS and EW dias, NS usually greater]					
77								
78								
79								
80								
81								
82	V. Tone Hole Depths							
83	f2	32.7						
84	e	28						
85	d	29	D tone holes drilled at fairly extreme angle					
86								
87	c	27.8						
88	b	25.6						
89	a	26.9						
90	g	15.8	meas along bot tone hole wall [north wall, toward reed,tone hole usually at angle]					
91	f1	19.9	meas along east side tone hole wall [north wall, toward reed,t hole usually at angle]					
92								
93	e1	9.5	e1 tone hole depth;meas east/west with deapth gauge [at center, or shortest dist]					
94	d1	9.4	d1 tone hole depth; meas east/west with depth gauge [at center, or shortest dist]					
95	c1	10.9	c1 tone hole depth; meas east/west with deapth gauge [at center, or shortest dist]					
96								
97								
98								
99								
100								
101	VI. Long Joint		Porthaux2 a table along long joint					
102	lg length	604	total length of long joint					

Porthaux2-O-Kampmann-Wg1-WOB-DNM

	A	B	C	D	E	F	G	H
103	lg_tenon_bot	53	length bottom tenon on long joint [tenon going into boot joint]					
104	lj_bot_bore	25.5	long joint bottom tenon bore diameter [tenon going into boot joint]					
105	lj_top_bore	33.4	long joint top tenon bore diameter [tenon going into bell]					
106	lg_tenon_top	37.1	length top tenon on long joint [tenon going into bell]					
107	e1_distance	60	dist long joint tenon to e1 [from bot of tenon to where tone hole enters bore]					
108	d1_distance	267	dist long joint tenon to d1 [from bot of tenon to where tone hole enters bore]					
109	c1_distance	482	dist long joint tenon to c1 [from bot of tenon to where tone hole enters bore]					
110								
111								
112								
113								
114								
115	VII. Bore diameters at Tone Holes							
116	f2	12.2						
117	e	13.2						
118	d	13.6						
119								
120	c	16.2						
121	b	17.3						
122	a	17.4						
123	g	20.4						
124	f1	22.6						
125								
126	e1	26.6	e1 tone hole bore diameter on long joint					
127	d1	29.6	d1 tone hole bore diameter on long joint					
128	c1	31.8	c1 tone hole bore diameter on long joint					
129								
130								
131								
132								
133								
134	VIII. Bell							
135	bell_logic	0	If bell_logic = 0 => normal conical bore; if bell_logic = 1 => inverted conical bore					
136	bell_length (0, 1, 2)	334	total length of bell [lines 141 + 144 = line 136]					
137	bell_bot_bore (0, 1, 2)	34.6	dia bore at the bottom of bell [end with socket]					
138	bell_top_bore 0, (1, 0, 2)	34.8	dia bore at the top of bell [where low Bb exits]					
139	bell_center_bore (only for logic 2)		dia bore at max center of expansion					
140	bell_wall (only for logic 2)		bell wall thickness, Just for David					
141	bell_bot_bore_expansion (only for logic 2)		dist of bottom to maxium of expansion [including bell socket length,if bell_logic=0 =>100]					
142	Outside diameter of wood at expansion		Just for David					
143	bell_tenon (0, 1, 0, 2)	38.2	bell socket length					
144	bell_expansion_length (only for logic 2)		distance of maxium expansion to top of bell [where Bb exits]					
145	bellfg	38.5	Usually about 10mm more than line 138					
146								
147								
148	IX. PITCH							
149	pitch	430	input the historical pitch of the bassoon, must input value, best guess					
150	freq_init	380	Initial frequency range variable					
151	Delta frequency	2	frequency increment parameter					
152	Number of frequencies	60	number of frequencies to scan for min chi sq					
153	Frequency adjust	1.05	frequency adjustment parameter					
154	X. Title							
155	title		Bassoon Calculation: Porthaux2-O-Kampmann-Wg1-WOB-DNM					
156								
157			Notes on long joint bore: Porthaux2 very out of round in places					
158			Notes on boot joint bore: Porthaux2 small side very out of round					
159	XI. Bore Diameter Locations							
160		21	Number of diameters					
161	Bell Bore	9.1	Initial bore diameter					
162	34.6mm diameter at socket	382	dist1; measured from the bottom of the wing joint- 10mm					1
163	34.8mm diameter at bell end	345	dist2; measured from the bottom of the wing joint- 11mm					1
164		295	dist3; measured from the bottom of the wing joint- 12mm					1
165		225	dist4; measured from the bottom of the wing joint- 13mm					1
166		142	dist5; measured from the bottom of the wing joint- 14mm					1
167		16	dist6; measured from the bottom of the wing joint- 15mm	Bottom wing joint	15.5			1
168		80	dist7; measured from the top of the bootjoint - small bore side- 16mm	top boot small	15.1			2
169		137	dist8; measured from the top of the bootjoint - small bore side- 17mm	top boot large	24.4			2
170		0	dist9; measured from the top of the bootjoint - small bore side- 18mm					2
171		383	dist10; measured from the top of the bootjoint - large bore side- 19mm	sbore dia sep	17.8			3
172		358	dist11; measured from the top of the bootjoint - large bore side- 20mm	lbore dia sep	19			3
173		275	dist12; measured from the top of the bootjoint - large bore side- 21mm					3
174		208	dist13; measured from the top of the bootjoint - large bore side- 22mm					3
175		143	dist14; measured from the top of the bootjoint - large bore side- 23mm					3
176		110	dist15; measured from the top of the bootjoint- large bore side- 24mm	lj_bot_bore	25.5			3
177		0	dist16; measured from the top of the long joint- 25mm					4
178		570	dist17; measured from the top of the long joint- 26mm					4
179		520	dist18; measured from the top of the long joint- 27mm					4
180		452	Porthaux2 OOR; dist19; measured from the top of the long joint- 28mm					4
181		385	dist20; measured from the top of the long joint- 29mm					4
182		305	dist21; measured from the top of the long joint- 30mm					4
183		237	Porthaux2 OOR; dist22; measured from the top of the long joint- 31mm					4
184		112	Porthaux2 OOR; dist23; measured from the top of the long joint- 32mm	li_top_bore	33.4			4